

# CFP TECHNOLOGIES

Tel:0828570324

Email: Info@cfptechnologies.co.za

[www.cfptechnologies.co.za](http://www.cfptechnologies.co.za)



## Veichi AC310 Motor Setup

- 1 Connect electrical motor to VFD as per instructions. Connect mains wiring to VFD.
- 2 Turn power on.

3 Motor Parameters. Set the following:

Parameter	Parameter Description	Value
F02.01	Motor number of poles	
F02.02	Motor rated power in kW	
F02.03	Motor rated Frequency Hz as per plate	
F02.04	Motor rated speed RPM	
F02.05	Motor rated voltage V	
F02.06	Motor rated current A	

4 Run Motor Parameter "Auto Tuning"

4a If auto tuning can be run without a load (preferable) use table below

Parameter	Parameter Description	Value
F02.07	Motor auto tuning	1

Enter F02.07. Change the value to 1. Press "set". Press RUN on the VFD control panel.  
Wait for the display to go back to the ready state.(Can take up to a few minutes)

Or

4b If auto tuning has to be run with a load use table below

Parameter	Parameter Description	Value
F02.07	Motor auto tuning	2

Enter F02.07. Change the value to 2. Press "set". Press RUN on the VFD control panel.  
Wait for the display to go back to the ready state.(Can take up to a few minutes)