

# CFP TECHNOLOGIES

Reg. no. 1987/027414/23

P.O Box 15740

Sinoville

0129

Tel:0828570324

Fax:0865278634

Email: Info@cfptechnologies.co.za

[www.cfptechnologies.co.za](http://www.cfptechnologies.co.za)



## Veichi AC300

### Pushbutton switch Configuration

**Step 1** Connect power and motor to VFD. Test FWD and Stop functions from VFD control panel

**Step 2** Connect external inputs as per diagram and change the following parameters on Veichi AC300

Parameter	Parameter Description	Value
F02.00	X1 Forward Run	1
F02.01	X2 Reverse Run	2
F02.02	X3 Stop	3
F02.23	3 wire configuration	2
F00.02	Terminal command	1
F00.03	External Potentiometer	2

#### Optional settings

Parameter	Value
F00.09	Maximum Frequency in Hz
F00.11	Upper Limit Frequency
F00.12	Lower limit Frequency in Hz
F00.14	Acceleration Time in seconds
F00.15	Deceleration time in seconds

